



Bluetooth dongle

- Support A2DP, HFP (Narrowband, Wideband)
- Support SBC, aptX, aptX-LL
- Support SPP high speed, ideally for ANC filter data transmission
- Support RSSI, Power and other information upload
- Support up and down, volume, pause / answer, and other key feedback
- Support recording, replaying, listening key feedback
- Support USB program control for automated test design

General specifications

U980 parameters	
Speaker Channel Number	2
Mic Channel Number	1
Working Voltage/Power Dissipation	5V/55mA
Dimensions(mm)	96*33*140
Interface Type	BNC
Suitable Temperature	-20°C~50°C
Bluetooth Command Control	USB

General features

- With a complete function of the configuration interface
- The audio codecs can be set
- Full audio profile support
- SPP high speed transmission capability
- RF transmitter power can be set
- Connect by mac address or auto connect BT device
- Through a variety of standard certification, in line with international standards

Audio specifications

Audio parameters	
Profile Versions	A2DPv1.2/AVRCPv1.4/HFPv1.6
RF Power	Typical max +8 dBm
A2DP Audio Codecs	SBC/aptX/aptX-LL
HFP Audio Codecs	CVSD/mSBC
Speaker/Mic Channel Amplitude	Max 0.8Vp



MegaSig reserves the right to change specifications and accessories without notice.



www.megasig.com

Shenzhen MegaSig Measurement & Control Technology Co.,Ltd

Tel: 0755-8950.8393

Fax: 0755-8950.8392

Sales email: sale@megasig.com

Technical support email: support@megasig.com

Address: Room 1002, Unit 2, Building 1, Hongxing Chuangzhi Plaza, Guangming District, Shenzhen, China